About this item

- 9500 Running Watts and 12500 Peak Watts (Gasoline); 8500 Running Watts, 11200 Peak Watts (Propane); Remote Start With Included Key Fob, Electric and Recoil Start; Up to 12 Hours of Run Time on a 6. 6 Gallon Fuel Tank With Fuel Gauge
- Features Two GFCI 120V 5–20R Standard Household Receptacle, One Transfer Switch Ready 120V L14-30R, and One RV Ready 120/240V 14–50R; All Outlets Have Rubber Covers for Added Safety
- Powered by a Heavy Duty 457cc Westinghouse 4-Stroke OHV Engine Featuring a Long-Lasting Cast Iron Sleeve With Automatic Low Oil Shutdown and Digital Hour Meter. VFT display gives you real time updates with the voltage output, frequency, and lifetime hours
- Plug-and-Play: Comes With a Remote Start Key Fob, 12V Battery Charger, Oil, an Oil Funnel, a Tool Kit, and a User's Manual to Get You Started Right Out of the Box (Minimal Assembly Required)
- All Westinghouse Portable Generators are Functionally Tested in the Factory and May Contain Minimum Residual Oil and/or Fuel Odor; EPA and CARB Compliant; Backed by 3-Year Limited Service, Labor, and Parts Coverage with Nationwide Customer Service Network



Product description

The Westinghouse WGen9500DF Dual Fuel Portable Generator produces up to 12, 500 peak watts and 9, 500 running watts, the WGen9500DF is a dual fuel generator that operates on gasoline or propane (LPG). The heavy duty 457cc 4-Stroke OHV Westinghouse Engine is constructed of a durable cast iron sleeve and runs for up to 12 hours on a 6. 6 gallon (25 L) gas tank, keeping you powered through the day with built-in fuel gauge, automatic low oil shutdown, and GFCI outlets. Push-Button Electric Start makes starting the WGen9500DF effortless while the remote start key fob offers added ease from a distance. Its intuitive control panel spotlights the Transfer Switch Ready L14-30R and larger 14-50R to power your major appliances like the air conditioner, refrigerator, and sump pump as well as any lights or entertainment centers all at the same time with a single cord hookup. VFT Data Center displays volt output, frequency, and lifetime hours to keep you up to date with real-time information and regular maintenance. Conveniently portable with an included set of heavy duty never-flat wheels, handle, and lift bracket, it'll have your house, travel trailer, or jobsite powered in seconds. The WGen9500DF is complete with 3-Year limited service, labor, and parts coverage with Lifetime Technical Support backed by our nationwide customer service and support network.

Features & Specs	
Wattage	12500 watts
Fuel Type	Gasoline, Propane
Power Source	Gas Powered
Recommended Uses For Product	Residential
Voltage	120 Volts
Output Wattage	12500
Additional Features	Dual Fuel, Electric Start, Fuel Gauge, Hour Meter, Low Oil Shutdown, Portable, Remote Start
Engine Type	4 Stroke
Ignition System Type	Electronic
Tank Volume	6 Gallons
Engine Displacement	457 Cubic Centimeters
Runtime	12 hours
Total Power Outlets	3
Frequency	60 Hz
Current Rating	50 Amps
Starting Wattage	9500 Watts
Running Wattage	9500 Watts